

Digital Panel Meter – Digital Ammeter

SYCON-9920 & SYCON 9923

Order code	Description
SYCON 9920	Single Phase Ammeter
SYCON 9923	Three Phase Ammeter

General Features

- Friendly user interface
- Easy to install
- SYCON 9920 available with single input current
- SYCON 9923 available with three input current (For phase input current)

Electrical Specifications

Auxiliary Supply	230Vac \pm 10%.
Frequency	50Hz \pm 5%.
Input Current	/5A
Accuracy	Class1 (\pm 1digit).
Range	Maximum 1600 Amp.
DIP selector switch	Located on the rare side of the meter for setting the desired current range from 100A to 1600A in steps of 100 A.